

| Battery Type   | LiFePO4 (16s/51.2V) | Setting Range |
|--|---------------------|---------------|
| Over Voltage Disconnect Voltage(OVD)<br>过压断开点          | ■ 60.00V    □ ____V | 36~68V        |
| Charging Limit Voltage(CLV)<br>充电限制点                   | ■ 58.00V    □ ____V | 36~68V        |
| Over Voltage Reconnect Voltage(OVR)<br>过压恢复点           | ■ 58.00V    □ ____V | 36~68V        |
| Equalization Charging Voltage (ECV)<br>均充电压            | ■ 57.60V    □ ____V | 36~68V        |
| Boost Charging Voltage (BCV)<br>快充电压                   | ■ 57.60V    □ ____V | 36~68V        |
| Float Charging Voltage (FCV)<br>浮充电压                   | ■ 55.20V    □ ____V | 36~68V        |
| Boost Voltage Reconnect (BVR)<br>快充重充点                 | ■ 52.80V    □ ____V | 36~68V        |
| Low Voltage Reconnect Voltage(LVR)<br>低电压恢复点           | ■ 51.20V    □ ____V | 36~68V        |
| Under Voltage Warning Recover Voltage(UVWR)<br>低压报警恢复点 | ■ 51.20V    □ ____V | 36~68V        |
| Under Voltage Warning Voltage(UVW)<br>低压报警点            | ■ 48.00V    □ ____V | 36~68V        |
| Low Voltage Disconnect Voltage (LVD)<br>低压断开点          | ■ 46.00V    □ ____V | 36~68V        |
| Discharging Limit Voltage(DLV)<br>放电限制电压               | ■ 46.00V    □ ____V | 36~68V        |
| Boosting Charing time<br>快充时间长度                        | □ 90m    □ ____min  | 0~180m        |
| Equalization Charing time<br>均充                        | □ 90m    □ ____min  | 0~180m        |
| LiBattery Protection<br>锂电池保护                          | □ Enable            |               |
| Lower Temperature Charging Limit<br>低温充电极限             | ■ 0°C    □ ____°C   | +10~-40°C     |
| Lower Temperature Discharging Limit<br>低温放电极限          | ■ -10°C    □ ____°C | +10~-40°C     |